

Intelligent Reflecting Surface vs. Decode-and-Forward: How Large Surfaces Are Needed to Beat Relaying?

Emil Björnson, *Senior Member, IEEE*, Özgecan Özdoğan, *Student Member, IEEE*, Erik G. Larsson, *Fellow, IEEE*

Abstract—The rate and energy efficiency of wireless channels can be improved by deploying software-controlled metasurfaces to reflect signals from the source to destination, especially when the direct path is weak. While previous works mainly optimized the reflections, this letter compares the new technology with classic decode-and-forward (DF) relaying. The main observation is that very high rates and/or large metasurfaces are needed to outperform DF relaying, both in terms of minimizing the total transmit power and maximizing the energy efficiency, which also includes the dissipation in the transceiver hardware.

Index Terms—Intelligent reflecting surface, DF relaying.

I. INTRODUCTION


A reflectarray is a surface that “reflects” an impinging plane wave in the shape of a beam or vice versa [1]. Different from parabolic reflectors, whose physical curvature and direction determine the beamforming pattern, a reflectarray is flat and consists of many small elements that scatter and phase-shift the impinging waves differently [2]. Reflectarrays with real-time reconfigurable phase, amplitude, and polarization properties have recently gained interest in mobile communications, under names such as *intelligent reflecting surface (IRS)* [3], [4] and *software-controlled metasurfaces* [5]–[7]. The main idea is to support the transmission from a source to a destination by adapting the propagation environment; that is, to configure the IRS to beamform its received signal towards the destination.

This is the same use case as for half-duplex relays [8], with the key difference that a relay actively processes the received signal before retransmitting an amplified signal, while an IRS passively reflects the signal without amplification but with beamforming. The relay achieves a higher signal-to-noise ratio (SNR) at the cost of a pre-log penalty due to the two-hop transmission. A comparison with an ideal amplify-and-forward (AF) relay was made in [9], showing large energy efficiency gains by using an IRSs. However, decode-and-forward (DF) relaying is known to outperform AF relaying in terms of achievable rates [10] and is thus a better benchmark.


In this letter, we try to make a fair comparison between IRS-supported transmission and repetition-coded DF relaying, with the purpose of determining how large an IRS needs to be to outperform conventional relaying. To this end, we optimize both technologies by computing the optimal transmit powers and the optimal number of elements in an IRS.

II. SYSTEM MODEL

We consider communication from a single-antenna source to a single-antenna destination. The deterministic flat-fading



(a) Intelligent reflecting surface (IRS) supported transmission.



(b) Relay-supported transmission.

Fig. 1: Illustration of the two setups considered in this paper.

channel is denoted by $h_{sd} \in \mathbb{C}$. The received signal at the destination is

$$y = h_{sd}\sqrt{p}s + n, \quad (1)$$

where p is the transmit power, s is the unit-power information signal, and $n \sim \mathcal{N}_{\mathbb{C}}(0, \sigma^2)$ is the receiver noise. For notational convenience, the antenna gains are included in the channels. The capacity of this single-input single-output (SISO) channel is

$$R_{\text{SISO}} = \log_2 \left(1 + \frac{p|h_{sd}|^2}{\sigma^2} \right). \quad (2)$$

The capacity can potentially be increased by involving additional equipment in the communication. In this paper, we consider two such setups: An IRS that is configured to “reflect” the signal towards the destination or a relay that operates in DF mode. The respective achievable rates (also known as spectral efficiencies) are derived below and then optimized analytically to enable a fair comparison. However, we stress that the choice of system model is biased in favor of the IRS; in particular, the assumption of deterministic flat-fading channels is ideal for an IRS since it is less capable of handling channel estimation and frequency-selective fading than relays.

The paper was supported by ELLIIT and Swedish Research Council.

The authors are with the Department of Electrical Engineering (ISY), Linköping University, SE-58183 Linköping, Sweden {emil.bjornson,ozgecan.ozdogan,erik.g.larsson}@liu.se.

A. IRS-supported Transmission

In this setup, we have an IRS with N discrete elements, as illustrated in Fig. 1(a). The deterministic channel from the source to the IRS is denoted by $\mathbf{h}_{\text{sr}} \in \mathbb{C}^N$, where $[\mathbf{h}_{\text{sr}}]_n$ denotes the n th component. The channel between the IRS and the destination is denoted by $\mathbf{h}_{\text{rd}} \in \mathbb{C}^N$. Each element has a smaller or comparable size to the wavelength, thus it scatters the incoming signal in many directions. The IRS's properties are therefore fully represented by the diagonal matrix

$$\Theta = \alpha \text{diag}(e^{j\theta_1}, \dots, e^{j\theta_N}), \quad (3)$$

where $\alpha \in (0, 1]$ is the fixed amplitude reflection coefficient and $\theta_1, \dots, \theta_N$ are the phase-shift variables that can be optimized by the IRS. Following the modeling in prior work (e.g., [3], [9], [11]), the received signal at the destination is

$$y = (h_{\text{sd}} + \mathbf{h}_{\text{sr}}^T \Theta \mathbf{h}_{\text{rd}}) \sqrt{p}s + n, \quad (4)$$

where p , s , and n are defined as in the SISO case. Since the channels are deterministic, the destination knows them perfectly and the phase-shift variables can be optimized.¹

Lemma 1. *The channel capacity of the IRS-supported network is*

$$\begin{aligned} R_{\text{IRS}}(N) &= \max_{\theta_1, \dots, \theta_N} \log_2 \left(1 + \frac{p|h_{\text{sd}} + \mathbf{h}_{\text{sr}}^T \Theta \mathbf{h}_{\text{rd}}|^2}{\sigma^2} \right) \\ &= \log_2 \left(1 + \frac{p(|h_{\text{sd}}| + \alpha \sum_{n=1}^N |[\mathbf{h}_{\text{sr}}]_n| |[\mathbf{h}_{\text{rd}}]_n|)^2}{\sigma^2} \right). \end{aligned} \quad (5)$$

Proof: For any given Θ , the rate expression in (5) is achieved from the capacity of an additive white Gaussian noise channel. Notice that $\mathbf{h}_{\text{sr}}^T \Theta \mathbf{h}_{\text{rd}} = \alpha \sum_{n=1}^N e^{j\theta_n} [\mathbf{h}_{\text{sr}}]_n [\mathbf{h}_{\text{rd}}]_n$. The maximum rate, which is the capacity, is achieved when the phase-shifts are selected as $\theta_n = \arg(h_{\text{sd}}) - \arg([\mathbf{h}_{\text{sr}}]_n [\mathbf{h}_{\text{rd}}]_n)$ to give every term in the sum the same phase as h_{sd} .² ■

B. Relay-supported Transmission

In this alternative setup, we make use of a half-duplex relay that is deployed at the same location as the IRS. This setup is illustrated in Fig. 1(b). We consider the classic repetition-coded DF relaying protocol where the transmission is divided into two equal-sized phases. In the first phase, the source transmits and the received signal at the destination is

$$y_{1d} = h_{\text{sd}} \sqrt{p_1} s + n_{1d}, \quad (7)$$

where p_1 is the transmit power, s is the unit-power information signal, and $n_{1d} \sim \mathcal{N}_{\mathbb{C}}(0, \sigma^2)$ is the receiver noise. In the same phase, the received signal at the relay is

$$y_{1r} = h_{\text{sr}} \sqrt{p_1} s + n_{1r}, \quad (8)$$

where $h_{\text{sr}} \in \mathbb{C}$ denotes the channel between the source and relay, while $n_{1r} \sim \mathcal{N}_{\mathbb{C}}(0, \sigma^2)$ is the receiver noise. The DF relay uses y_{1r} to decode the information and then encodes it again for transmission in the second phase. Note that the relay

can be compact; an antenna, transceiver chains, and a baseband unit fit into the dimensions of a small mobile phone.

In the second phase, the relay transmits $\sqrt{p_2} s$ and the received signal at the destination is

$$y_{2d} = h_{\text{rd}} \sqrt{p_2} s + n_{2d}, \quad (9)$$

where p_2 is the transmit power, $h_{\text{rd}} \in \mathbb{C}$ denotes the channel between the relay and destination, while $n_{2d} \sim \mathcal{N}_{\mathbb{C}}(0, \sigma^2)$ is the receiver noise. By utilizing (7) and (9) for maximum ratio combining, the following rate is achievable at the destination.

Lemma 2. *The achievable rate with repetition-coded DF relaying is*

$$R_{\text{DF}} = \frac{1}{2} \log_2 \left(1 + \min \left(\frac{p_1 |h_{\text{sr}}|^2}{\sigma^2}, \frac{p_1 |h_{\text{sd}}|^2}{\sigma^2} + \frac{p_2 |h_{\text{rd}}|^2}{\sigma^2} \right) \right). \quad (10)$$

Proof: This is a classical result found in [8, Eq. (15)]. ■

Remark 1. *For brevity, the analysis in this letter assumes deterministic channels, but the extension to fading channels with perfect channel knowledge is straightforward: we only need to take expectations of the rate expressions in (6) and (10). Hence, all the conclusions apply to this case as well.*

III. ANALYTICAL PERFORMANCE COMPARISON

In this section, we compare the three achievable rates that were presented in Section II. Interestingly, the expressions only depend on the amplitudes of the channel elements, but not on their phases. For brevity, we introduce the notation $|h_{\text{sd}}| = \sqrt{\beta_{\text{sd}}}$, $|h_{\text{sr}}| = \sqrt{\beta_{\text{sr}}}$, $|h_{\text{rd}}| = \sqrt{\beta_{\text{rd}}}$, and $\frac{1}{N} \sum_{n=1}^N |[\mathbf{h}_{\text{sr}}]_n| |[\mathbf{h}_{\text{rd}}]_n| = \sqrt{\beta_{\text{IRS}}}$. We can now rewrite (2), (6), and (10) in the more compact forms

$$R_{\text{SISO}} = \log_2 \left(1 + \frac{p\beta_{\text{sd}}}{\sigma^2} \right), \quad (11)$$

$$R_{\text{IRS}}(N) = \log_2 \left(1 + \frac{p(\sqrt{\beta_{\text{sd}}} + N\alpha\sqrt{\beta_{\text{IRS}}})^2}{\sigma^2} \right), \quad (12)$$

$$R_{\text{DF}} = \frac{1}{2} \log_2 \left(1 + \min \left(\frac{p_1\beta_{\text{sr}}}{\sigma^2}, \frac{p_1\beta_{\text{sd}}}{\sigma^2} + \frac{p_2\beta_{\text{rd}}}{\sigma^2} \right) \right). \quad (13)$$

It is obvious that $R_{\text{IRS}}(N) \geq R_{\text{SISO}}$ since equality is achieved for $N = 0$ and $R_{\text{IRS}}(N)$ is an increasing function of N . In fact, the rate grows as $\mathcal{O}(\log_2(N^2))$ when N is large, as previously noted in [3] and further explained in [13]. The comparison between the IRS and DF relay cases is non-trivial. To make it fair, we first select p_1 and p_2 optimally, while having the same average power p as when using the IRS.

Proposition 1. *Assume that $p_1, p_2 \geq 0$ are selected under the constraint $p = \frac{p_1 + p_2}{2}$. If $\beta_{\text{sd}} > \beta_{\text{sr}}$, it holds that $R_{\text{SISO}} > R_{\text{DF}}$ for any selection of p_1, p_2 , thus DF relaying is suboptimal.*

If $\beta_{\text{sd}} \leq \beta_{\text{sr}}$, the rate with DF relaying is maximized by $p_1 = \frac{2p\beta_{\text{rd}}}{\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}}}$ and $p_2 = \frac{2p(\beta_{\text{sr}} - \beta_{\text{sd}})}{\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}}}$, leading to

$$R_{\text{DF}} = \frac{1}{2} \log_2 \left(1 + \frac{2p\beta_{\text{rd}}\beta_{\text{sr}}}{(\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}})\sigma^2} \right). \quad (14)$$

Proof: If $\beta_{\text{sd}} > \beta_{\text{sr}}$, $\min \left(\frac{p_1\beta_{\text{sr}}}{\sigma^2}, \frac{p_1\beta_{\text{sd}}}{\sigma^2} + \frac{p_2\beta_{\text{rd}}}{\sigma^2} \right) = \frac{p_1\beta_{\text{sr}}}{\sigma^2}$, which is maximized by $p_1 = 2p$ and $p_2 = 0$. Hence, the relay

¹Channel estimation is non-trivial for IRS-supported transmissions, but some recent methods are found in [12].

²This proof idea follows the same main steps as in [3, Sec. III.B].

is not used and obviously $R_{\text{SISO}} > R_{\text{DF}}$. If $\beta_{\text{sd}} \leq \beta_{\text{sr}}$, R_{DF} is maximized by selecting p_1, p_2 to achieve $\frac{p_1 \beta_{\text{sr}}}{\sigma^2} = \frac{p_1 \beta_{\text{sd}}}{\sigma^2} + \frac{p_2 \beta_{\text{rd}}}{\sigma^2}$ under the constraint $p = \frac{p_1 + p_2}{2}$. This gives a linear system of equations with the solution that is stated in the proposition. ■

One important implication of Proposition 1 is that the relay-supported network needs to switch between two modes: SISO transmission and DF relaying. It is only when the channel from the source to the relay is stronger than the direct path from the source to destination (i.e., $\beta_{\text{sr}} \geq \beta_{\text{sd}}$) that DF relaying might provide $R_{\text{DF}} > R_{\text{SISO}}$.

Proposition 2. *The IRS-supported transmission provides the highest rate for any $N \geq 1$ if $\beta_{\text{sd}} > \beta_{\text{sr}}$. In the case $\beta_{\text{sd}} \leq \beta_{\text{sr}}$, it provides the highest rate if and only if*

$$N > \frac{\sqrt{\left(\sqrt{1 + \frac{2p\beta_{\text{rd}}\beta_{\text{sr}}}{(\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}})\sigma^2}} - 1\right) \frac{\sigma^2}{p}} - \sqrt{\beta_{\text{sd}}}}{\alpha\sqrt{\beta_{\text{IRS}}}}. \quad (15)$$

Proof: Since $R_{\text{IRS}}(N) > R_{\text{SISO}}$ for $N \geq 1$, the IRS-supported case gives the highest rate if and only if $R_{\text{IRS}}(N) > R_{\text{DF}}$. This always occurs for $\beta_{\text{sd}} > \beta_{\text{sr}}$ since $R_{\text{SISO}} > R_{\text{DF}}$ due to Proposition 1. If $\beta_{\text{sd}} \leq \beta_{\text{sr}}$, the inequality $R_{\text{IRS}}(N) > R_{\text{DF}}$ can be simplified to (15) by utilizing (12) and (14). ■

To interpret the result in Proposition 2, we now consider that there is line-of-sight to and from the IRS. It is reasonable to assume that all elements in \mathbf{h}_{sr} have the same magnitude as h_{sr} , and all elements in \mathbf{h}_{rd} have the same magnitude as h_{rd} . Consequently, $\beta_{\text{IRS}} = \beta_{\text{sr}}\beta_{\text{rd}}$. We first notice that although IRS-supported transmission provides the highest rate for $\beta_{\text{sd}} > \beta_{\text{sr}}$, the difference between $R_{\text{IRS}}(N)$ and R_{SISO} is small in this case since $\sqrt{\beta_{\text{sd}}} \gg N\alpha\sqrt{\beta_{\text{IRS}}} = N\alpha\sqrt{\beta_{\text{sr}}\beta_{\text{rd}}}$ for most practical values of N because β_{rd} is a very small number in practice; note that a ‘‘large’’ channel gain in wireless communications is -60 dB. Hence, it is in the case $\beta_{\text{sd}} \leq \beta_{\text{sr}}$ that an IRS can provide an appreciable performance gain.

The right-hand side of (15) depends on the transmit SNR p/σ^2 , the amplitude reflection coefficient α , and the channel gains β_{sd} , β_{sr} , and β_{rd} (recall that $\beta_{\text{IRS}} = \beta_{\text{sr}}\beta_{\text{rd}}$). Note that the right-hand side approaches $-\frac{\sqrt{\beta_{\text{sd}}}}{\alpha\sqrt{\beta_{\text{sr}}\beta_{\text{rd}}}}$ as $p \rightarrow \infty$, which implies that the IRS-supported transmission achieves the largest rate at high SNR for any N . In contrast, the inequality in (15) becomes

$$N > \frac{\sqrt{\frac{1}{(\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}})} - \frac{\sqrt{\beta_{\text{sd}}}}{\sqrt{\beta_{\text{sr}}\beta_{\text{rd}}}}}}{\alpha}. \quad (16)$$

as $p \rightarrow 0$, which can be a very large number if $\beta_{\text{sd}} \ll \beta_{\text{sr}}$. For example, (16) becomes $N > 963$ for $\alpha = 1$, $\beta_{\text{sd}} = -110$ dB, $\beta_{\text{sr}} = -80$ dB, and $\beta_{\text{rd}} = -60$ dB.

In summary, the choice between an IRS and a relay depends on the SNR and number of elements. In Section IV, we assess if practical setups operate in the low or high SNR regime; that is, if any of the asymptotic results above can be applied.

A. Transmit Power Minimization Under Rate Constraints

If the destination requires a particular data rate \bar{R} , the rate expressions in (11)–(14) can be used to identify the required transmit power for each of the three communication setups.

Corollary 1. *To achieve a data rate \bar{R} , the SISO case requires the power*

$$p_{\text{SISO}} = \left(2^{\bar{R}} - 1\right) \frac{\sigma^2}{\beta_{\text{sd}}}, \quad (17)$$

the IRS-supported transmission requires the power

$$p_{\text{IRS}}(N) = \left(2^{\bar{R}} - 1\right) \frac{\sigma^2}{(\sqrt{\beta_{\text{sd}}} + N\alpha\sqrt{\beta_{\text{IRS}}})^2}, \quad (18)$$

and the relay-supported transmission requires the power

$$p_{\text{DF}} = \begin{cases} \left(2^{2\bar{R}} - 1\right) \frac{\sigma^2}{\beta_{\text{sd}}} & \text{if } \beta_{\text{sd}} > \beta_{\text{sr}}, \\ \left(2^{2\bar{R}} - 1\right) \frac{(\beta_{\text{sr}} + \beta_{\text{rd}} - \beta_{\text{sd}})\sigma^2}{2\beta_{\text{rd}}\beta_{\text{sr}}} & \text{if } \beta_{\text{sd}} \leq \beta_{\text{sr}}. \end{cases} \quad (19)$$

If the relay-supported system switches between SISO and DF relaying mode to minimize the transmit power, its required transmit power is $p_{\text{DFmode}} = \min(p_{\text{SISO}}, p_{\text{DF}})$.

B. Total Power Minimization Under Rate Constraints

The total power consumption, P_{total} , of the system consists of both transmit power and dissipation in hardware components. In the SISO case, it is $P_{\text{total}}^{\text{SISO}} = p_{\text{SISO}}/\nu + P_s + P_d$, where $\nu \in (0, 1]$ is the efficiency of the power amplifier while P_s and P_d are the hardware-dissipated power at the source and destination, respectively. In the IRS case, it becomes [9]

$$P_{\text{total}}^{\text{IRS}}(N) = \frac{p_{\text{IRS}}(N)}{\nu} + P_s + P_d + NP_e, \quad (20)$$

where P_e is the power dissipation per element, which is caused by the circuitry required for adaptive phase-shifting. In the relaying case, the source is only active half of the time, thus

$$P_{\text{total}}^{\text{DF}} = \frac{p_{\text{DF}}}{\nu} + \frac{1}{2}P_s + P_d + P_r, \quad (21)$$

where P_r is the hardware-dissipated power at the relay.

Proposition 3. *Suppose β_{IRS} is a constant independent of N . For a given data rate \bar{R} , the total power $P_{\text{total}}^{\text{IRS}}(N)$ when using an IRS is a convex function and minimized by*

$$N^{\text{opt}} = \sqrt[3]{\frac{(2^{\bar{R}} - 1)\sigma^2}{\alpha^2\beta_{\text{IRS}}P_e}} - \frac{1}{\alpha}\sqrt{\frac{\beta_{\text{sd}}}{\beta_{\text{IRS}}}}. \quad (22)$$

Proof: The function is convex since $\frac{\partial^2}{\partial N^2} P_{\text{total}}^{\text{IRS}}(N) > 0$. The solution (22) is then obtained from $\frac{\partial}{\partial N} P_{\text{total}}^{\text{IRS}}(N) = 0$. ■

The optimal number of elements in (22) is generally not an integer number, thus the true optimum is either the closest smaller or larger integer. The optimum can also be negative, making the SISO case with $N = 0$ the true optimum. One example when β_{IRS} is independent of N is the line-of-sight case with $\beta_{\text{IRS}} = \beta_{\text{sr}}\beta_{\text{rd}}$ described in the previous subsection.³

³If $[\mathbf{h}_{\text{sr}}]_n [\mathbf{h}_{\text{rd}}]_n$ for $n = 1, \dots, N$ are realizations from independent and identically distributed random variables, then $\beta_{\text{IRS}} \rightarrow \mathbb{E}\{[\mathbf{h}_{\text{sr}}]_n [\mathbf{h}_{\text{rd}}]_n\}$ as $N \rightarrow \infty$ due to the law of large numbers. The upper bound could equal $\sqrt{\beta_{\text{sr}}\beta_{\text{rd}}}$ since the IRS is deployed at the same location as the relay.




Fig. 2: Typical channel gains as a function of the distance, when including the antenna gains $G_t = G_r = 5$ dBi.

IV. NUMERICAL PERFORMANCE COMPARISON

We will now compare the systems numerically. The channel gains are modeled using the 3GPP Urban Micro (UMi) from [14, Table B.1.2.1-1] with a carrier frequency of 3 GHz. We use the line-of-sight (LOS) and non-LOS (NLOS) versions of UMi, which are defined for distances ≥ 10 m. We let G_t and G_r denote the antenna gains (in dBi) at the transmitter and receiver, respectively. We neglect shadow fading to get a deterministic model and show the channel gain β as a function of the distance d in Figure 2:

$$\begin{aligned} \beta(d) \text{ [dB]} \\ = G_t + G_r + \begin{cases} -37.5 - 22 \log_{10}(d/1 \text{ m}) & \text{if LOS,} \\ -35.1 - 36.7 \log_{10}(d/1 \text{ m}) & \text{if NLOS.} \end{cases} \end{aligned} \quad (23)$$

We included Fig. 2 to reinforce the point that a seemingly small number such as -60 dB is actually a *very large* channel gain, while typical numbers are in the range -70 to -110 dB.

We consider the simulation setup in Fig. 3, where the source and IRS/relay are deployed at fixed locations, while the location of the destination is determined by the variable d_1 . We use (23) to compute the channel gains based on the distances, assuming 5 dBi antennas at the source and IRS/relay, while the destination is a handset with an omnidirectional antenna with 0 dBi. The IRS and relay are deployed to have LOS channels to the source, and the destination has a LOS channel to the IRS/relay. We can therefore assume $\beta_{\text{IRS}} = \beta_{\text{sr}}\beta_{\text{rd}}$. Moreover, there is an NLOS channel between the source and destination, which leads to a weaker channel gain and motivates the use of an IRS or relay to support the transmission.

Fig. 4 shows the transmit power that is needed to achieve a rate of either $\bar{R} = 4$ bit/s/Hz or $\bar{R} = 6$ bit/s/Hz. The bandwidth is $B = 10$ MHz, the corresponding noise power is -94 dBm, and $\alpha = 1$. The figure shows results for the SISO case, DF relaying (without mode selection), and an IRS with $N \in \{25, 50, 100, 150\}$. In the case of $\bar{R} = 4$ bit/s/Hz, the SISO case requires the highest power while the DF relaying case requires the least power at all the considered locations of the destination. The transmit power required in the IRS case reduces as N increases and the gap to the DF relaying case is smallest when the destination is either close to the source or to the IRS. By using (15), we obtain that $N > 164$ is required if the IRS should outperform DF relaying when $d_1 = 80$ m.






Fig. 3: The simulation setup where d_1 is a variable.



(a) $\bar{R} = 4$ bit/s/Hz.



(b) $\bar{R} = 6$ bit/s/Hz.

Fig. 4: The transmit power needed to achieve the rate \bar{R} in the scenario shown in Fig. 3, as a function of the distance d_1 .

Higher transmit powers are needed in Fig. 4(b), where the rate is increased to $\bar{R} = 6$ bit/s/Hz. The IRS case becomes more competitive; it requires the least power when the destination is close to the source, while “only” $N > 76$ is needed to outperform relaying when $d_1 = 80$ m. The reason that relaying loses some of its advantages is that it must have a higher SINR than in the IRS case due the $1/2$ -prelog penalty; thus, the required power grows more rapidly with \bar{R} with relaying.

A. Energy Efficiency

It was shown in [9] that an IRS can improve the energy efficiency (EE), which is defined as $B \cdot \bar{R}/P_{\text{total}}$. We will make a similar analysis using the models in Sec. III-B with $\nu = 0.5$, $P_s = P_d = P_r = 100$ mW, $P_e = 5$ mW [9], and $d_1 = 70$ m. Fig. 5 shows the EE as a function of \bar{R} . The number of elements in the IRS, N , is optimized for maximal EE using Proposition 3. The SISO case provides the highest EE for $\bar{R} \in (0, 3.47]$ bit/s/Hz, while the DF relaying case provides the highest EE for $\bar{R} \in (3.47, 8.48]$ bit/s/Hz. It is only for $\bar{R} > 4.9$ bit/s/Hz that the IRS has $N^{\text{opt}} > 0$ and it is only for $\bar{R} > 8.48$ bit/s/Hz that it provides higher EE




Fig. 5: The energy efficiency as a function of the rate \bar{R} .

than DF relaying. Hence, a system that switches between the SISO and DF relaying modes is preferable both in terms of minimizing the transmit power and maximizing the energy efficiency, except when very high rates are required.

V. CONCLUSION AND DISCUSSION

We have compared classic repetition-coded DF relaying with the new concept of IRSs. The key observation is that an IRS needs hundreds of reconfigurable elements (each of the size of an antenna) to be competitive—even if we considered ideal phase-shifting and frequency-flat channels, which are two assumptions that clearly benefit the IRS. The reason is that the source’s transmit power must travel over two channels to reach the destination, leading to a very small channel gain $\beta_{sr}\beta_{rd}$ per element in the IRS—the SNR becomes almost the same as for amplify-and-forward relaying *without amplification*. Hence, the IRS needs many elements are needed to compensate for the low channel gain. In contrast, with DF relaying, we first transmit over a channel with gain β_{sr} and then transmit again over a channel with gain β_{rd} . While the large surface area is a weakness for IRSs, the advantage is that an IRS requires no power amplifiers in its ideal form; however, in practice, active components are needed for adaptive phase-shifting. Even if the power dissipation per element is low, the total power is non-negligible. An IRS only achieves higher EE than DF relaying if very high rates are needed. Note that we only considered repetition-coded DF relaying, but other DF protocols achieve higher rates by optimizing the coding of the two hops and, thus, are even more competitive against an IRS-supported transmission [15].

The fact that the source is physically separated from the IRS is the key feature—it allows for controlling the propagation environment—but also the reason for the large pathlosses. Classical reflectarrays are using nearby sources equipped with high-gain horn antennas to manage the pathloss [2]. Alternatively, one could deploy the source behind the IRS, within the wall, without a wireless channel between them [6]; this is known as holographic beamforming [16]. Both approaches solve the pathloss issue but lack the key feature of the IRS.

REFERENCES

[1] J. Huang, *Reflectarray Antenna*. John Wiley & Sons, Inc., 2005.
 [2] D. M. Pozar, S. D. Targonski, and H. D. Syrigos, “Design of millimeter wave microstrip reflectarrays,” *IEEE Trans. Antennas Propag.*, vol. 45, no. 2, pp. 287–296, 1997.

[3] Q. Wu and R. Zhang, “Intelligent reflecting surface enhanced wireless network via joint active and passive beamforming,” *CoRR*, vol. abs/1810.03961, 2018.
 [4] —, “Towards smart and reconfigurable environment: Intelligent reflecting surface aided wireless network,” *CoRR*, vol. abs/1905.00152, 2019.
 [5] C. Liaskos, S. Nie, A. Tsioliariidou, A. Pitsillides, S. Ioannidis, and I. Akyildiz, “A new wireless communication paradigm through software-controlled metasurfaces,” *IEEE Commun. Mag.*, vol. 56, no. 9, pp. 162–169, 2018.
 [6] E. Björnson, L. Sanguinetti, H. Wymeersch, J. Hoydis, and T. L. Marzetta, “Massive MIMO is a reality—What is next? Five promising research directions for antenna arrays,” *Digital Signal Processing*, 2019, to appear.
 [7] M. D. Renzo, M. Debbah, D.-T. Phan-Huy, A. Zappone, M.-S. Alouini, C. Yuen, V. Sciancalepore, G. C. Alexandropoulos, J. Hoydis, H. Gacanin, J. de Rosny, A. Bounceu, G. Lerosey, and M. Fink, “Smart radio environments empowered by reconfigurable AI metasurfaces: an idea whose time has come,” *EURASIP Journal on Wireless Communications and Networking*, vol. 2019:129, 2019.
 [8] J. N. Laneman, D. N. C. Tse, and G. W. Wornell, “Cooperative diversity in wireless networks: Efficient protocols and outage behavior,” *IEEE Trans. Inf. Theory*, vol. 50, no. 12, pp. 3062–3080, 2004.
 [9] C. Huang, A. Zappone, G. C. Alexandropoulos, M. Debbah, and C. Yuen, “Reconfigurable intelligent surfaces for energy efficiency in wireless communication,” *CoRR*, vol. abs/1810.06934, 2018.
 [10] G. Farhadi and N. C. Beaulieu, “On the ergodic capacity of multi-hop wireless relaying systems,” *IEEE Trans. Wireless Commun.*, vol. 8, no. 5, pp. 2286–2291, 2009.
 [11] Q. Nadeem, A. Kammoun, A. Chaaban, M. Debbah, and M.-S. Alouini, “Asymptotic analysis of large intelligent surface assisted MIMO communication,” *CoRR*, vol. abs/1903.08127, 2019.
 [12] Z.-Q. He and X. Yuan, “Cascaded channel estimation for large intelligent metasurface assisted massive mimo,” *CoRR*, vol. abs/1905.07948, 2019.
 [13] E. Björnson and L. Sanguinetti, “Demystifying the power scaling law of intelligent reflecting surfaces and metasurfaces,” *CoRR*, vol. abs/1908.03133, 2019.
 [14] *Further advancements for E-UTRA physical layer aspects (Release 9)*. 3GPP TS 36.814, Mar. 2010.
 [15] M. N. Khormuji and E. G. Larsson, “Cooperative transmission based on decode-and-forward relaying with partial repetition coding,” *IEEE Trans. Commun.*, vol. 8, no. 4, pp. 1716–1725, 2009.
 [16] E. J. Black, “Holographic beam forming and MIMO,” Pivotal Commware, Tech. Rep., 2017. [Online]. Available: <https://pivotalcommware.com/wp-content/uploads/2017/12/Holographic-Beamforming-WP-v.6C-FINAL.pdf>