

Supplementary text

Let x_j and x_k be two signals of length T such that they only differ of a time shift t_0 . In this simple situation, their cross-spectrum in the continuous domain reads as

$$P_{jk}(e^{i\omega}) = P_j(e^{i\omega})e^{i\omega t_0} \quad (1)$$

where ω is the angular frequency of a signal [?]. In the discrete domain, this can be rewritten as

$$P_{jk}[f] = P_j[f]e^{i2\pi f t_0/T} \quad (2)$$

where the time shift t_0 becomes a linear phase term.
In the mathematical formulation of coherence C

$$C_{jk}[f] = \frac{|P_{jk}[f]|}{(P_j[f] \cdot P_k[f])^{1/2}} \quad (3)$$

the numerator is the real part of the cross-spectrum and the exponential term in Eq. 2 is canceled out. This indicates that C values do not depend on the amount of time shift between the signals.

Instead, in imaginary coherence IC ,

$$IC_{jk}[f] = \frac{|\Im(P_{jk}[f])|}{(P_j[f] \cdot P_k[f])^{1/2}} \quad (4)$$

it is trivial to show that there is a remaining term related to t_0 in the numerator. Indeed, by rewriting the cross-spectrum via trigonometric functions:

$$P_{jk}[f] = P_j[f](\cos(2\pi f t_0/T) + i \sin(2\pi f t_0/T)) \quad (5)$$

Hence, by taking the imaginary part one obtains

$$\Im(P_{jk}[f]) = P_j[f] \sin(2\pi f t_0/T) \quad (6)$$

This indicates that IC values do depend on the relative delay between the signals in a very specific way. More in general, in it has been emphasized that the estimated imaginary coherency between two time series can be expressed as a function of the instantaneous phase difference of their analytic signals [1].

References

1. Stam CJ, Nolte G, Daffertshofer A. Phase lag index: assessment of functional connectivity from multi channel EEG and MEG with diminished bias from common sources. Human brain mapping. 2007;28(11):1178–1193.