

The optimal structure of the MRPC detector for 0.511 MeV gamma based on Monte Carlo simulation

J. Liu,^a Y. Wang,^{a,1} B. Guo^a D. Han^a and Y. Li^a

^aKey Laboratory of Particle and Radiation Imaging, Department of Engineering Physics, Tsinghua University, Beijing 100084, China

E-mail: liu-jn20@mails.tsinghua.edu.cn

ABSTRACT: Detailed detector simulations can not only optimize the structure of the detector by analyzing the performance, but also provide strong support for the experimental design. To obtain the optimal structure of Multi-gap Resistive Plate Chambers (MRPCs) for 0.511 MeV gammas, a complete simulation framework for gamma detection by the MRPCs based on Geant4 and Magboltz software is described in this paper. The simulation shows how gamma interacts with MRPCs and the process of gas ionization, avalanche multiplication, and signal formation. The simulation results are in good agreement with the experimental results. By analyzing the time resolution and detection efficiency, the optimal structure of MRPCs for 0.511 MeV gammas is proposed.

KEYWORDS: Detector modelling and simulations II (electric fields, charge transport, multiplication and induction, pulse formation, electron emission, etc) ; Gaseous detectors

¹Corresponding author.

Contents

1	Introduction	1
2	Simulation framework for gamma detection by MRPC	1
3	Results of the simulation and comparison with experimental data	4
4	The optimal structure of MRPC for 0.511 MeV gamma	5
5	Conclusion	7

1 Introduction

The Multigap Resistive Plate Chamber (MRPC) is a spark-protected gas detector with good time resolution and low cost. In 1996, a team led by Williams proposed MRPC [1] for the first time based on the Resistive Plate Chamber (RPC). Essentially, the single millimeter-scale wide gas gap of RPC is divided into multiple narrow gas gaps with a width of hundreds of micrometers through glass electrodes. The narrow gas gap enables the Townsend avalanche to occur within a very small space, enhancing the avalanche's initial Townsend coefficient through intensified electric fields, ultimately refining time resolution without compromising detection efficiency. MRPC has excellent time resolution [2, 3] and good spatial resolution [4], making MRPC Time-of-Flight Positron Emission Tomography (TOF-PET) a promising application prospect.

Currently, international research on the simulation of gamma detection by the MRPC mainly focuses on studying the relationship between the number of gas gaps, the thickness of the converter, and the detection efficiency[5, 6]. However, there is a lack of detailed simulation specifically addressing the time resolution, which is of utmost importance for MRPC TOF-PET. Therefore, in this paper, we have established a comprehensive simulation framework for detecting gamma rays by MRPCs. This framework encompasses the entire simulation process, from detector construction and particle generator setup to energy deposition modeling, avalanche multiplication calculation, induced signal generation, waveform shaping, and ultimately, data storage and analysis. Using this framework, we have conducted detailed studies on the time resolution and detection efficiency of various detector structures, ultimately proposing an optimized structure optimized for 0.511 MeV gamma rays.

2 Simulation framework for gamma detection by MRPC

The MRPC detector is built in Geant4, including the geometry and material configuration. A basic structure of the MRPC is shown in figure 1. Nylon fishing lines create uniform gaps between the glass plates. Mylar layers are used to separate the graphite high-voltage layer from the printed circuit

board (PCB). Honeycomb panels are used to support and protect the detector. In the simulation, parameters such as the number of chambers and gaps, the thickness of the resistive plates and gas gaps can be changed as needed. The source of particles can be defined as any type, with any energy, placed at any position, and emitted in any direction.




Figure 1. Schematic drawing of the cross-section of a basic MRPC detector.

In this paper, the particle source is defined as 0.511 MeV gamma, incident in the direction perpendicular to the detector. Figure 2 shows the visual interface in the Geant4 simulation. The green tracks are gamma photons and the red tracks are electrons. It can be seen that the electrons entering the gas gaps ionize along the direction of the inverse electric field, and disappear after reaching the anode.




Figure 2. Visualization interface in Geant4 simulation. (a) overall, (b) local amplification.

Because the gas gap thickness of the MRPC detector is generally in the order of several hundred microns, the Photo Absorption Ionization (PAI) model in Geant4 is chosen for energy deposition in thin sensors. The interaction between charged particles and extranuclear electrons is accomplished by emitting and absorbing virtual photons, and the range of virtual photons is the reaction cross section, so the ionization energy loss can be calculated by using the photo-absorption data of ultraviolet and X-ray interactions with matter, which is in good agreement with the experimental data. Electrons from the Gamma photon interacting with the MRPC detector drift towards the anode and start the avalanche multiplication. The Avalanche follows the Townsend multiplication

law [7]. The change of the average number of electrons in the gas gap with the drift distance is:

$$\frac{d\bar{n}}{dx} = (\alpha - \eta) \bar{n} \quad (2.1)$$

where α is the Townsend coefficient, η is the attachment coefficient and \bar{n} is the number of electrons at position x . The Townsend coefficient, the attachment coefficient, the effective Townsend coefficient, and the drift velocity are calculated by Magboltz, as shown in figure 3.




Figure 3. (a) Townsend coefficient, (b) attachment coefficient, (c) effective Townsend coefficient and (d) drift velocity calculated by Magboltz.

The induced current on the readout electrodes follows the Ramo theory [8], see (2.2).

$$i(t) = \frac{E_w \cdot v}{V_w} e_0 N(t), \quad \frac{E_w}{V_w} = \frac{\varepsilon}{ng\varepsilon + (n+1)d} \quad (2.2)$$

where v is the drift velocity of electrons, e_0 is the electron charge, $N(t)$ is the number of electrons in the gas gap at time t , and E_w is the weighting field, whose value is equal to the electric field

when the potential of the readout electrode is set to V_w and others 0. The value of $\frac{E_w}{V_w}$ is related to the geometry of the detector and the material of the resistive plate. n is the number of gas gaps, g and d are the thickness of the gas gap and the resistive plate respectively, ε is the relative dielectric constant of the resistive plate.

Taking the 4-gap MRPC with 0.4 mm gap thickness as an example, the change of induced current with time is shown in figure 4. In the simulation, the signal can be represented as the convolution of the original induced current $i(t)$ and a simplified electronics response $f(t)$.

$$V(t) = i(t) \otimes f(t), \quad f(t) = A \left(e^{-\frac{t}{\tau_1}} - e^{-\frac{t}{\tau_2}} \right) \quad (2.3)$$




Figure 4. (a) Original induced current, (b) The signal convoluted with readout electronics response.

where A is the amplification factor of the electronics, and τ_1 and τ_2 correspond to the time constants of the RC circuits in the electronics. τ_1 and τ_2 affect the length of the leading and trailing edge of the output signal, and thus these values should be calibrated according to the electronics used in the experiment. Figure 4(b) is the same example as figure 4(a), and its shape is very similar to the real waveform. In the experiment, the electronics and all the cables will bring noise to the MRPC signal. In the simulation, a Gaussian noise is used to simulate it, and the σ of the noise is consistent with the experiment.

3 Results of the simulation and comparison with experimental data

To evaluate the effectiveness of the simulation, the simulation and experimental data of two different MRPC detectors with two kinds of readout systems are compared. Two 4-chamber 32-gap MRPC prototypes with 0.128 mm gap thickness are fabricated and tested. The time resolution of 193 ps FWHM and the induced charge of 43 fC for 0.511 MeV photons are obtained using the fast front-end amplifier and the Tektronix oscilloscope. The simulation conditions correspond to the experiment.




Figure 5. The relationship between time difference and signal amplitude before (a) and after (b) time walk correction, and the distribution of time difference before (c) and after (d) time walk correction obtained by the experiment of 4-chamber 32-gap MRPCs.

The time resolution is 190 ps FWHM and the induced charge is 50 fC, which is consistent with the experimental results.

In addition, the simulation and experimental results of 4-gap MRPC with 0.4 mm gap thickness are compared. The simulated time resolution is 616 ps FWHM and the induced charge is 146.3 fC, which is consistent with the experimental results of 665 ps FWHM and 158.4 fC measured by the fast front-end amplifier and waveform digitizer system.

4 The optimal structure of MRPC for 0.511 MeV gamma

The working electric field of MRPC detectors with different structures is calculated by Magboltz software, as shown in figure 7. The intrinsic time resolution and detection efficiency of MRPC with different structures are simulated as shown in figure 8. As the gas gap thickness decreases and the number of gas gaps diminishes, the intrinsic time resolution improves significantly, albeit at the cost of reduced detection efficiency. Specifically, when the gas gap thickness falls below 0.13 mm, the detection efficiency plummets due to the inadequate signal amplitude generated. Therefore, balancing the need for exceptional time resolution with adequate detection efficiency, the optimal




Figure 6. The relationship between time difference and signal amplitude before (a) and after (b) time walk correction, and the distribution of time difference before (c) and after (d) time walk correction obtained by the simulation of 4-chamber 32-gap MRPCs.

detector configuration comprises a single chamber with eight gas gaps, each measuring 0.13 mm in thickness. This design ensures an optimal trade-off between performance metrics.

The relationship between the detection efficiency, the induced charge of the MRPC detector and the thickness of the resistive plate is simulated. The results reveal an intriguing trend: as the thickness of the resistive plate increases, the detection efficiency initially exhibits an upward surge, followed by a gradual decline. The induced charge consistently decreases with the augmentation of the resistive plate's thickness. Based on these findings, the optimal thickness for the resistive plate is determined to be 0.4 mm




Figure 7. The working electric field of MRPC detectors.




Figure 8. The intrinsic time resolution (a) and detection efficiency (b) of MRPC with different structures.

5 Conclusion

We have developed a comprehensive simulation framework for the gamma detection by MRPCs, and it has been confirmed that the simulation results are in good agreement with the experimental results obtained by using a ^{22}Na radioactive source. This simulation framework can be utilized to optimize detector design. For 0.511 MeV gammas, balancing time resolution and detection efficiency, the optimal detector structure is determined to be 1-chamber 8-gap MRPC with 0.13 mm gas gap thickness and 0.4 mm resistive plate thickness. Additionally, the simulated complete signal waveforms provide a foundation for further improving the time resolution through the reconstruction




Figure 9. Results of detection efficiency and induced charge of MRPC detector with different resistive plate thickness.

of time using algorithms such as machine learning.

Acknowledgments

The work is supported by the National Natural Science Foundation of China under Grant No. 11927901, 11420101004, 11461141011, 11275108, 11735009 and U1832118. This work is also supported by the Ministry of Science and Technology under Grant No. 2020YFE0202001, 2018YFE0205200 and 2016YFA0400100.

References

- [1] E.C. Zeballos, I. Crotty, D. Hatzifotiadou, J.L. Valverde, S. Neupane, M. Williams et al., *A new type of resistive plate chamber: the multigap rpc*, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment* **374** (1996) 132.
- [2] K. Ackermann, N. Adams, C. Adler, Z. Ahammed, S. Ahmad, C. Allgower et al., *Star detector overview*, *Nuclear Instruments and Methods in Physics Research Section A: Accelerators, Spectrometers, Detectors and Associated Equipment* **499** (2003) 624.
- [3] A. Akindinov, A. Alici, A. Agostinelli, P. Antonioli, S. Arcelli, M. Basile et al., *Performance of the alice time-of-flight detector at the lhc*, *The European Physical Journal Plus* **128** (2013) 1.
- [4] L. Shi, Y. Wang, X. Huang, X. Wang, W. Zhu, Y. Li et al., *A high time and spatial resolution mrpc designed for muon tomography*, *Journal of Instrumentation* **9** (2014) C12038.
- [5] M. Nizam, B. Satyanarayana, R. Shinde and G. Majumder, *Development and characterization of six-gap glass mrpcs and feasibility study of a pet device*, *arXiv preprint arXiv:1907.09379* (2019) .
- [6] Z. Weizheng, S. Ming, L. Cheng, C. Hongfang, S. Yongjie and C. Tianxiang, *Monte carlo simulation of rpc-based pet with geant4*, *arXiv preprint arXiv:1402.4544* (2014) .
- [7] J. Townsend, *The conductivity produced in gases by the motion of negatively-charged ions*, *Nature* **62** (1900) 340.

[8] S. Ramo, *Currents induced by electron motion*, *Proceedings of the IRE* **27** (1939) 584.