



Fig. 4. Wind profiles. From the top: Area 1 (DK1), Area 2 (DK2), Area 3 (SE1) and Area 4 (SE4) [4], [5].

VII. TRANSMISSION SYSTEM

The internal network of each area is a meshed AC grid with 31 overhead lines, 2 cables and 5 transformers (see Fig. II). Transmission network data is obtained from the IEEE RTS '96 Test System [1] and listed in Table VII. Only continuous line ratings are considered.

The four area are interconnected by the following AC and HVDC tie-lines:

- 400 kV VSC-HVDC line connecting bus # 106 and bus # 203;
- 250 kV VSC-HVDC line connecting bus # 123 and bus # 323;
- 350 kV VSC-HVDC line connecting bus # 121 and bus # 422;
- 230 kV AC line connecting bus # 222 and bus # 317;
- 138 kV AC line connecting bus # 307 and bus # 403;
- 230 kV AC line connecting bus # 313 and bus # 415;
- 230 kV AC line connecting bus # 323 and bus # 417;

The four AC interconnectors are adopted from [1], their data is listed in Table VIII. The base power is 100 MW and the base voltage 230 kV (except for line 307-403, for which the base voltage is 138 kV).

Three HVDC interconnectors are connecting Area 1 to the other areas. The base power is 100 MW and the base voltages (DC side) respectively 400 kV, 250 kV and 350 kV. The converter station losses are represented with the generalized loss model [6], [7]:

$$p_{conv}^{loss} = a |I_{conv}|^2 + b |I_{conv}| + c, \quad (2)$$

where a , b and c are numerical parameters reflecting the quadratic, linear and constant dependence of the losses on the line current and $|I_{conv}|$ is the magnitude of the current flowing

through the converter. The data of HVDC interconnectors is derived from [7] and listed in Table IX.

It is worth mentioning that, since Area 1 is connected to the other areas only through HVDC lines, the whole system can represent two asynchronous areas (Area 1 and Area 2-4).

TABLE VII
LINE DATA

ID	FROM BUS	TO BUS	R (pu)	X (pu)	B (pu)	Rating (MVA)	Transf ratio
C01	1	2	0.003	0.014	0.461	175	0
L01	1	3	0.055	0.211	0.057	175	0
L02	1	5	0.022	0.085	0.023	175	0
L03	2	4	0.033	0.127	0.034	175	0
L04	2	6	0.050	0.192	0.052	175	0
L05	3	9	0.031	0.119	0.032	175	0
T01	3	24	0.002	0.084	0.000	400	1.03
L06	4	9	0.027	0.104	0.028	175	0
L07	5	10	0.023	0.088	0.024	175	0
C02	6	10	0.014	0.061	2.459	175	0
L08	7	8	0.016	0.061	0.017	175	0
L09	8	9	0.043	0.165	0.045	175	0
L10	8	10	0.043	0.165	0.045	175	0
T02	9	11	0.002	0.084	0.000	400	1.03
T03	9	12	0.002	0.084	0.000	400	1.03
T04	10	11	0.002	0.084	0.000	400	1.02
T05	10	12	0.002	0.084	0.000	400	1.02
L11	11	13	0.006	0.048	0.100	500	0
L12	11	14	0.005	0.042	0.088	500	0
L13	12	13	0.006	0.048	0.100	500	0
L14	12	23	0.012	0.097	0.203	500	0
L15	13	23	0.011	0.087	0.182	500	0
L16	14	16	0.005	0.039	0.082	500	0
L17	15	16	0.002	0.017	0.036	500	0
L18	15	21	0.006	0.049	0.103	500	0
L19	15	21	0.006	0.049	0.103	500	0
L20	15	24	0.007	0.052	0.109	500	0
L21	16	17	0.003	0.026	0.055	500	0
L22	16	19	0.003	0.023	0.049	500	0
L23	17	18	0.002	0.014	0.030	500	0
L24	17	22	0.014	0.105	0.221	500	0
L25	18	21	0.003	0.026	0.055	500	0
L26	18	21	0.003	0.026	0.055	500	0
L27	19	20	0.005	0.040	0.083	500	0
L28	19	20	0.005	0.040	0.083	500	0
L29	20	23	0.003	0.022	0.046	500	0
L30	20	23	0.003	0.022	0.046	500	0
L31	21	22	0.009	0.068	0.142	500	0

TABLE VIII
AC INTERCONNECTOR DATA

LINE ID	FROM BUS	TO BUS	R (pu)	X (pu)	B (pu)	Rating (MVA)
AC01	222	317	0.013	0.104	0.218	500
AC02-1	307	403	0.042	0.161	0.044	175
AC02-2	313	415	0.010	0.075	0.158	500
AC02-3	323	417	0.010	0.074	0.155	500

TABLE IX
HVDC INTERCONNECTOR DATA

LINE ID	FROM BUS	TO BUS	R (pu)	a_{inv} (pu)	a_{rec} (pu)	b (pu)	c (pu)	Rating (MW)
DC01	106	203	.0080	.0005	.0003	.0007	.0074	80
DC02	123	323	.0036	.0056	.0019	.0013	.0015	400
DC03	121	422	.0037	.0049	.0019	.0012	.0015	600