



# CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Fujitsu Siemens Computers  
PRIMERGY BX630, AMD Opteron (TM) 875

SPECint\_rate2000 = 35.6  
SPECint\_rate\_base2000 = 32.7

SPEC license #: 22 | Tested by: Fujitsu Siemens Computers | Test date: Jan-2006 | Hardware Avail: Oct-2005 | Software Avail: Mar-2004

Benchmark	Base Copies	Base Runtime	Base Ratio	Copies	Runtime	Ratio
164.gzip	2	116	27.9	2	116	27.9
175.vpr	2	117	27.9	2	113	28.8
176.gcc	2	67.7	37.7	2	67.9	37.6
181.mcf	2	205	20.3	2	163	25.6
186.crafty	2	70.1	33.1	2	63.7	36.4
197.parser	2	131	31.8	2	131	31.8
252.eon	2	76.8	39.3	2	54.4	55.5
253.perlbnk	2	124	33.7	2	114	36.5
254.gap	2	72.9	35.0	2	72.9	35.0
255.vortex	2	82.4	53.5	2	75.3	58.5
256.bzip2	2	129	27.0	2	126	27.6
300.twolf	2	199	35.0	2	170	40.9

### Hardware

CPU: AMD Opteron (TM) 875 processor (2.20 GHz)  
 CPU MHz: 2200  
 FPU: Integrated  
 CPU(s) enabled: 2 cores, 1 chip, 2 cores/chip  
 CPU(s) orderable: 1,2,4  
 Parallel: No  
 Primary Cache: 64KBI + 64KBD on chip, per core  
 Secondary Cache: 1024KB (I+D) on chip, per core  
 L3 Cache: N/A  
 Other Cache: N/A  
 Memory: 4x2048MB DDR-RAM PC3200R CL3-3-3  
 Disk Subsystem: Western Digital WD2500 (SATA, 7.2krpm)  
 Other Hardware: None

### Software

Operating System: Windows Server 2003 Enterprise Edition + SP1  
 Compiler: Intel C++ 8.0  
 Build 20040318Z (for 32-bit applications),  
 Microsoft Visual Studio .Net 2003  
 7.1.3088 (for libraries),  
 SmartHeap Library Version 8.0  
 from <http://www.microquill.com>  
 File System: NTFS  
 System State: Default

## Notes/Tuning Information

### GENERAL

+FDO: PASS1= -Qprof\_gen PASS2= -Qprof\_use

### Portability flags

176.gcc: -Dalloca=\_alloca /F10000000  
 186.crafty: -DNT\_i386  
 253.perlbnk: -DSPEC\_CPU2000\_NTOS -DPERLDLL /MT  
 254.gap: -DSYS\_HAS\_CALLOC\_PROTO -DSYS\_HAS\_MALLOC\_PROTO

### Base tuning flags

for C programs: -fast -arch:SSE2 -Oi- +FDO  
 for C++ programs: -fast -GX -GR +FDO

### Peak tuning flags

164.gzip: basepeak=yes  
 175.vpr: -fast -arch:SSE2 -Qoption,c,-ip\_ninl\_max\_stats=2000,  
 -ip\_ninl\_max\_total\_stats=4500 +FDO ONESTEP=yes  
 176.gcc: -fast -arch:SSE2 -Oi- -Qunroll3 +FDO shlw32M.lib  
 181.mcf: -fast -QaxN +FDO shlw32M.lib  
 186.crafty: -fast -arch:SSE2 +FDO ONESTEP=yes shlw32M.lib



# CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Fujitsu Siemens Computers  
PRIMERGY BX630, AMD Opteron (TM) 875

SPECint\_rate2000 = 35.6  
SPECint\_rate\_base2000 = 32.7

SPEC license #: 22 | Tested by: Fujitsu Siemens Computers | Test date: Jan-2006 | Hardware Avail: Oct-2005 | Software Avail: Mar-2004

## Notes/Tuning Information (Continued)

```
197.parser: basepeak=yes
252.eon: -fast -arch:SSE2 -Qansi_alias -Qoption,c,-ip_ninl_max_stats=2000,
        -ip_ninl_max_total_stats=4500 +FDO ONESTEP=yes shlw32M.lib
253.perlbnk: -fast -arch:SSE2 -Oi- +FDO ONESTEP=yes shlw32M.lib
254.gap: basepeak=yes
255.vortex: -fast -arch:SSE -Oi- -Qoption,c,-ip_ninl_max_stats=2000,
        -ip_ninl_max_total_stats=4500 +FDO shlw32M.lib
256.bzip2: -fast -Qunroll2 shlw32M.lib
300.twolf: -fast -arch:SSE2 -Qansi_alias +FDO ONESTEP=yes shlw32M.lib
```

'start /b /wait /affinity' command is used to bind CPU(s) to processes

boot options: /Execute /NOPAE  
/USEPMTIMER

BIOS settings: Memory Timing: 1T  
DRAM Bank Interleave=AUTO

This result was measured with 32-bit binaries using the 32-bit version of the operating system.

For information about Fujitsu Siemens Computers in your country please see:  
<http://www.fujitsu-siemens.com/countries>